



Dimensions of assembled package:
11' 1" wide x 18' 9" deep x 10' 7" tall

The components of this gym can be combined with others to create different play sets. This is the best order of assembly to create this specific set.

Read this sheet and all instructions included with the different parts before assembly.

See the Instructions and Owner's Manual included in carton 63007-424 for important safety information.

Cartons for this Play Set:

1	63007-421	Lexington Box 1 (Hardware)
1	63007-422	Lexington Box 2
1	63007-423	Lexington Box 3
1	63007-424	Lexington Tent Roof (Hdwre & Instr)
1	SH946-102	Access Ladder, 5ft
1	8364-400	10ft. Scoop Slide
1	AH201-102Q	Rock Climbing Wall (Hdwre & Instr)
1	SD204-102Q	Lexington Picnic Table (Hdwre & Instr)
1	63090-222	Chain Climber Frame (Hdwre & Instr)
1	63089-606	Chain Cargo Net
1	SH922-800Q	Ramp (Hdwre & Instr)



- Start by assembling the Lexington tower. Instructions and hardware are in the cartons noted above.
- Wait to install the Access Ladder, Slide, and Wall Slats until after the rest of the play set is complete.
- Lex step 19. The swing mount is not needed.
- Lex step 20. Do not install the safety rail. It will be used on the picnic table.
- Install the Picnic Table (SD204-102Q).
- Install the Rock Climbing Wall (AH201-102Q) on the side shown.
- Secure the access ladder next to the rock climber using the method shown in step 18 of the Lexington instructions.
- Set the ramp and slide as shown above. Check spacing.
- Install the slide mount and slide using the method shown in steps 26 and 27 of the Lexington instructions.
- Install the Ramp (SH922-800Q) next to the slide.
- Assemble the Chain Climber on the left side of the gym using the instructions included in 63090-222.
- Install the wall slats in the positions shown above, using the methods from the Lexington Instructions. Gaps must be narrower than 3-1/2" or wider than 9" to prevent potential head entrapment.
- Mount the hand grips to the entrance wall slats.
- Double-check all fasteners are secure and all recessed hardware is covered by hole caps.